


# Model TE3201/2

## PXIe Based Single/Dual Channel 20GHz 30dBm RF Amplifier

Model TE3201/2 is a single/dual channel RF amplifier in a single slot PXIe form factor that can operate from 100kHz to 20GHz, designed for high frequency, and high power signal amplification. With an ultra-high bandwidth of almost 20GHz and up to +30dBm power into 50 ohms, the TE3201/2 is the ideal complimentary amplifier to any signal source that needs an extended power boost for demanding applications.



### Enhancing Performance

The TE3201/2 was designed to extend the power range of the Tabor arbitrary waveform generators and RF signal generators for applications, requiring a higher output power to drive their DUT (Device Under Test). With the channels cascaded the TE3201/2 can provide up to 25dB gain and can reach a maximum saturated power of 30dBm into 50 ohms loads, without compromising signal integrity.

### Cost Effective Versatile Solution

While the TE3201/2 was designed with the Tabor units in mind, it can be used as a standalone RF amplifier for any signal source. The TE3201/2 offers one or two channels in a compact and cost-effective solution for extending any signal source's power performance.

### Target Applications

Target applications for the TE3201/2 are diverse and include various RF applications, such as receiver testing, multi-tone testing, and general electronics and scientific applications. The new TE3201/2 is an ideal solution for virtually any wide bandwidth application that requires high power and high frequency signal amplification.

# Model TE3201/2

## Specifications

RF Characteristics			
<b>RF Connectors:</b>	2.92mm(K)		
<b>Frequency Range:</b>	100kHz to 20GHz		
<b>Gain (in dB): Single Channel in TE3201/2</b>	Min.	Typ.	Max.
100kHz to 100MHz:	10	12	14
100MHz to 3GHz:	10	12.5	13
3GHz to 9GHz:	8	10	11
9GHz to 20GHz:	6	8	9.5
<b>Gain (in dB): Cascaded Channels of TE3202</b>	Min.	Typ.	Max.
100kHz to 100MHz:	20	24	27
100MHz to 3GHz:	19.5	24.5	25.5
3GHz to 9GHz:	15	19	21
9GHz to 20GHz:	10.5	14.5	17.5
<b>Input Return Loss:</b>	14dB typ. (9dB Min.)		
<b>Output Return Loss:</b>	12dB typ. (6dB Min.)		
<b>P1dB:</b>	26dBm		
<b>Psat:</b>	29dBm		
<b>Output IP3:</b>	35dBm		
<b>Noise Figure:</b>	10dB		
<b>Reverse Isolation:</b>	50dB typ. (35dB Min.)		
<b>Second Harmonic:</b>	20dBc @ Pout +25 dBm		



<b>RF Input Power:</b>	
TE3201	20dBm Max.
TE3202	10dBm Max.
<b>Protection:</b>	Reverse Polarity, Over Voltage, Under Voltage, Over Current, and Open-Short Load

General	
<b>Voltage:</b>	+12V
<b>Current Consumption:</b>	
TE3201	+12V 1A
TE3202	+12V 2A
<b>Power Dissipation:</b>	
TE3201	11W typ.
TE3202	22W typ.
<b>Dimensions:</b>	Single slot PXLe
<b>Weight:</b>	
Without Package:	0.5 Kg
Shipping Weight:	1.5 Kg
<b>Temperature:</b>	
Operating:	0°C to +50°C
Storage:	-40°C to +70°C
<b>Warm up Time:</b>	15 minutes
<b>Humidity:</b>	85% RH, non-condensing
<b>Safety:</b>	CE Marked, IEC61010-1:2010
<b>EMC:</b>	IEC 61326-1:2013
<b>Calibration:</b>	2 years
<b>Warranty:</b>	3 years

Ordering Information	
<b>Model</b>	<b>Description</b>
TE3201	PXLe based single channel 20GHz
TE3202	PXLe based dual channel 20GHz 30dBm RF amplifier
CAS	Jumper cable for TE3202 for cascading CH1 and CH2

All rights reserved to Tabor Electronics Ltd. Tabor makes no representations nor warranties with respect to the accuracy or completeness of the contents and reserves the right to make changes at any time without notice. Ver. 1.4, revised November 10, 2024.